

J66K

Engine JOHN DEERE , 4045TF120
Alternator LEROY SOMER , LSA432M45

STANDARD FEATURES

- Mechanical governor
- Mechanically welded chassis with antivibration suspension
- Power circuit breaker
- Radiator for wiring T° of 50°C [122°F] max with mechanical fan
- Protective grille for fan and rotating parts
- 9dB(A) silencer supplied separately
- Charged DC starting battery with electrolyte
- 12 V charging alternator and starter
- Supplied with oil and coolant -30°C
- User manual and commissioning guide



Voltage	Power ESP kWe/kVA	Power PRP kWe/kVA	Standby Amps	Dimensions	Weight
415/240	53 / 66	48 / 60	92	Length: 1870mm [74in] Width: 994mm [39in] Height: 1360mm [54in]	1000kg [2205 lbs] Net 1210kg [2668 lbs] Gross
400/230	53 / 66	48 / 60	95		
380/220	53 / 66	48 / 60	100		
240/120	53 / 66	48 / 60	159		
230/115	53 / 66	48 / 60	166		
220/110	53 / 66	48 / 60	173		
220/127	53 / 66	48 / 60	173		
200/115	53 / 66	48 / 60	191		



POWER DEFINITION

PRP : Prime Power is available for an unlimited number of annual operating hours in variable load applications, in accordance with ISO 8528-1. A 10% overload capability is available for a period of 1 hour within 12-hour period of operation, in accordance with ISO 3046-1 –

ESP : The standby power rating is applicable for supplying emergency power in variable load applications in accordance with ISO 8528-1. Overload is not allowed.

TERM OF USE

Standard reference conditions 25 °C Air Inlet Temp, 3500 m A.S.L. 60 % relative humidity. All engine performance data based on the above mentioned maximum continuous ratings.

Type		dB(A)@1m	dB(A)@7m	Dimensions	Weight	Tank
	M128	75.6	66	Length: 2300mm [91in] Width: 1080mm [43in] Height: 1680mm [66in]	1410kg [3109lbs] Net 1610kg [3549lbs] Gross	180 L
	M128-DW	75.6	66	Length: 2344mm [92in] Width: 1080mm [43in] Height: 1900mm [75in]	1657kg [3653lbs] Net 2047kg [4513lbs] Gross	390 L





ENGINE SPECIFICATIONS

STANDARD FEATURES	Manufacturer / Model	JOHN DEERE 4045TF120 , 4-strokes, Turbo , [N/A] 4 X
	Cylinder Arrangement	L
	Displacement	4.48L [273.4C.I.]
	Bore and Stroke	106mm [4.2in.] X 127mm [5.0in.]
	Compression ratio	17 : 1
	Rated RPM	1500 Rpm
	Piston Speed	6.35m/s [20.8ft./s]
	Max. stand by Power at rated RPM	68kW [91BHP]
	Frequency regulation, steady state	+/- 2.5%
	BMEP	11.2bar [162psi]
	Governor : type	MECA
EXHAUST SYSTEM	Exhaust temperature	545°C [1013°F]
	Exhaust gas flow	176L/s [373cfm]
	Max back pressure	750mm CE [30in. WG]
FUEL SYSTEM	110% (Stand By power)	17.5L/h [4.6gal/hr]
	100% (of the Prime Power)	16L/h [4.2gal/hr]
	75% (of the Prime Power)	12L/h [3.2gal/hr]
	50% (of the Prime Power)	8.5L/h [2.2gal/hr]
	Max. fuel pump flow	108L/h [28.5gal/hr]
OIL SYSTEM	Total oil capacity w/filters	13.5L [3.6gal]
	Oil Pressure low idle	1bar [14.5psi]
	Oil Pressure rated RPM	5bar [72.5psi]
	Oil consumption 100% load	0.016L/h [0.004gal/hr]
	Oil capacity carter	12.5L [3.3gal]
THERMAL BALANCE	Heat rejection to exhaust	54kW [3070Btu/mn]
	Radiated heat to ambient	8kW [455Btu/mn]
	Heat rejection to coolant	35kW [1990Btu/mn]
AIR INTAKE	Max. intake restriction	625mm CE [25in. WG]
	Engine air flow	66L/s [140cfm]
COOLANT SYSTEM	Radiator & engine capacity	23.6L [6.2gal]
	Max water temperature	105°C [221°F]
	Outlet water temperature	93°C [199°F]
	Fan power	2 kW
	Fan air flow w/o restriction	2.53m ³ /s [5361cfm]
	Available restriction on air flow	20mm CE [0.8in. WG]
	Type of coolant	Gencool
	Thermostat	82-94 °C
EMISSIONS LEVEL	PM	60 mg/Nm ³
	CO	190 mg/Nm ³
	Nox	3800 mg/Nm ³
	HC	150 mg/Nm ³

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this CD Rom without notice, in a constant effort to improve the quality of its products.

SDMO Industries – 12bis rue de la Villeneuve – CS 92848 – 29 228 BREST CEDEX 2

Tel +33 (0)2 98 41 41 41 – Fax : +33 (0)2 98 41 63 07 – www.sdmo.com





ALTERNATOR SPECIFICATIONS

GENERAL DATAS	Manufacturer	LEROY SOMER
	Type	LSA432M45
	Number of phase	3
	Power factor (Cos Phi)	0.8
	Altitude	< 1000 m
	Overspeed	2250 rpm
	Pole : number	4
	Exciter type	SHUNT
	Insulation : class, temperature rise	H / H
	Voltage regulator	R230
	Total harmonics (TGH/THC)	< 2%
	Wave form : NEMA = TIF – TGH/THC	< 50
	Wave form : CEI = FHT – TGH/THC	< 2%
	Bearing : number	1
	Coupling	Direct
	Voltage regulation 0 to 100% load	+/- 0.5%
	Recovery time (20% Volt dip) ms	500 ms
SKVA with 90% of nominal sustained voltage (at 0.4PF)	N/A	
OTHER DATAS	Continuous nominal rating @ 40°C	60 kVA
	Standby rating @ 27°C	66 kVA
	Efficiencies @ 4/4 load	89 %
	Air flow	0.27m3/s [572.09cfm]
	Short circuit ratio;50 (Kcc)	0.39
	Direct axis synchro reactance unsaturated (Xd)	304 %
	Quadra axis synchro reactance unsaturated (Xq)	182 %
	Open circuit time constant;50 (T'do)	1270 ms
	Direct axis transient reactance saturated (X'd)	11.9 %
	Short circuit transient time constant (T'd)	50 ms
	Direct axis subtransient reactance saturated (X''d)	5.9 %
	Subtransient time constant (T''d)	5 ms
	Quadra axis subtransient reactance saturated (X''q)	7.4 %
	Zero sequence reactance unsaturated (Xo)	0.5 %
	Negative sequence reactance saturated (X2)	6.7 %
	Armature time constant (Ta)	8 ms
	No load excitation current (io)	0.4 A
	Full load excitation current (ic)	1.6 A
	Full load excitation voltage (uc)	30 V
	Recovery time (Delta U = 20% transitoire)	500 ms
	Motor start (Delta = 20% perm. Or 50% trans.)	156 kVA
	Transient dip (4/4 charge) – PF : 1.8 AR	15.5 %
	No load losses	1.12kW [1.12Kw]
	Heat rejection	5.89 kW



CONTROL PANEL

Standard



NEXYS

Specifications :

Frequency meter, Ammeter, Voltmeter
Alarms and faults Oil pressure, water temperature,
Overcrank, Overspeed (>60 kVA), Min/max alternator,
Low fuel level, Emergency stop
Engine parameters Hours counter, Engine speed,
Battery voltage, Fuel level, Air preheating

Option



TELYS

Specifications :

Frequency meter, Ammeter, Voltmeter
Alarms and faults Oil pressure, water temperature, No
start-up, Overspeed, Min/max alternator, Min/max
battery voltage, Low fuel level, Emergency stop
Engine parameters Hours counter, Oil pressure, Water
temperature, Engine speed, Battery voltage, Fuel level

